

## HAORI: RAS - B16N4KVRG-E

- Ultra quiet systems less than 19dB(A).
- Power supply to indoor or outdoor unit.
- Factory-integrated WI-FI with Energy monitoring.
- Fabrics with infinite possibilities , let your style be your guide.
- Toshiba Plasma Ionizer catches and neutralizes the contaminated particles.



Retail Price (interactive icons):



UK



ROI



Hi - Res Image

### HIGH TIER PRODUCT RANGE

CODE		45	
<b>Performance</b>			
Indoor Unit	RAS-		B16N4KVRG-E
Outdoor Unit	RAS-		<a href="#">16J2AVSG-E1</a>
Nominal	Cooling Capacity	kW	4.6
	Heating Capacity	kW	5.5
	EER/COP	W/W	3.41/3.62
UK	Cooling Total/Sensible	kW	4.49/3.42
	Heating	kW	3.37
Cooling EN14825	Range Min. - Max.	kW	1.20 - 5.30
	Power Input	kW	1.35
	Pdesign	kW	4.6
	SEER/Energy Efficiency Class		7.80/A++
	Seasonal Energy Consumption	kWh/a	206
Heating EN14825	Range Min. - Max.	kW	1.10 - 6.30
	Power Input	kW	1.52
	Pdesign	kW	4.0
	SCOP/Energy Efficiency Class		4.60/A++
	Seasonal Energy Consumption	kWh/a	1214

### Indoor Data

Air Flow	High - Low	l/s	262 - 93
	High - Low	m3/h	330 - 300
Sound	Pressure High - Low	dB(A)	45 - 22
	Power High - Low	dB(A)	59 - 34
Unit	Height x Width x Depth	mm	300x987x210
	Weight	kg	12
Pipe Connection	Flare Connections (gas - liquid)	inch	3/8" - 1/4"
	Drain Pipe Connection OD/ID	mm	16/14
Remote controller			WH-UA01UE

### Accessories

<a href="#">RB-I4101-E</a>	Fabric Cover Kit (supplied loose)	Fabric Dark Gray	
<a href="#">RB-I4102-E</a>	Fabric Cover Kit (supplied loose)	Fabric Light Gray	
<a href="#">RB-I4103-E</a>	Fabric Cover Kit (supplied loose)	Fabric Bluish Gray	
<a href="#">RB-I4104-E</a>	Fabric Cover Kit (supplied loose)	Fabric Gray Beige	
<a href="#">RB-I4105-E</a>	Fabric Cover Kit (supplied loose)	Fabric Dark Brown	
<a href="#">RB-I4106-E</a>	Fabric Cover Kit (supplied loose)	Fabric Emerald Blue	

\*All [Accessories / Controls](#)

### Related Items:

- [BIM Files](#)
- [CAD Files](#)
- [Full Specification](#)
- [Airflow/ Fan Curve](#)
- [Dimensional Drawing](#)
- [Wiring Diagram](#)
- [Installation Manual](#)
- [Owners Manual](#)

